

專業舞台音響系列

PROFESSIONAL AMPLIFIER

綜合擴音機

1. 輸出功率：80W + 80W。
2. 負載阻抗：4~16Ω。
3. 失真率：0.03%。
4. 信號雜音比：85dB。
5. 頻率響應：20Hz~20KHz。
6. A、B 組喇叭輸出。
7. 3 組麥克風輸入及音量調整。
8. 具迴音、REPEAT、DELAY、ECHO 調整。
9. 具備 4 組影音同步輸入。
10. 具備有自動接唱，當麥克風傳送信號時，自動將伴唱歌聲替換。
11. 具高、低音質調整。
12. 具音聲多重及響度控制功能。
13. 尺寸：430W * 410D * 162H (mm)。



KA-218

Professional Amplifier

1. Output power: 80W + 80W.
2. Load Impedance: 4 ~ 16Ω.
3. Distortion: 0.03%.
4. Signal to noise ratio: 85dB.
5. Frequency Response: 20Hz ~ 20KHz.
6. A, group B speaker outputs.
7. 3 microphone input and volume adjustments.
8. With echo, REPEAT, DELAY, ECHO adjustments.
9. With four groups audio and video synchronization input.
10. Equipped with automatic pick to sing, to send a signal when the microphone, singing accompaniment will be replaced automatically.
11. With high and low quality adjustments.
12. Having multiple and loudness control and audio functions.
13. Dimensions: 430W * 410D * 162H (mm).

專業擴大機

1. 立體輸出：
2* 125W(rms) at 8 Ω。
2* 200W(rms) at 4 Ω。
2. 橋接輸出：
250W(rms) at 16 Ω。
400W(rms) at 8 Ω。
3. 頻率響應：20Hz ~ 20KHz ±0.5dB。
4. 失真率：10Hz ~ 20KHz <0.2%。
5. 雜音比：>100dB。
6. 輸入阻抗：10KΩ/unbalance；20KΩ/balance。
7. 靈敏度：1.22V full power at 8 Ω。
8. 完善的保護電路：
(1) 直流電壓保護。(2) 超低頻保護。(3) 超載保護。(4) 短路保護。
(5) 過溫保護。
9. 兩個獨立通道採用分離電源供電，每個通道均有獨立的限幅，保護及 LED 指示電路。
10. 擴大機具有完備的輸入輸出孔：每個通道均提供一個 XLR 輸入插座和一個 Φ6.3 立體聲插孔，作為平衡式或非平衡式信號的輸入孔，每個通道均提供一個 SPEAKER 座和一對梅花型接線端子。
11. 採用靜音高轉速自動連續調速風扇冷卻系統，可根據散熱器的溫度自動調節風扇的轉速，保證良好的散熱。
12. 標準機櫃尺寸可直接按裝或放置於桌上。
13. 重量：22kg。
14. 尺寸：483W * 480D * 89H (mm)。



PN-250

Professional Amplifier

1. Stereo Output: 2* 125W(rms) at 8 Ω.
2* 200W(rms) at 4 Ω.
2. Bridge Output: 250W(rms) at 16 Ω.
400W(rms) at 8 Ω.
3. Frequency Response: 20Hz ~ 20KHz ±0.5dB.
4. T.H.D.: 10Hz ~ 20KHz <0.2%.
5. S/N Ratio: >100dB.
6. Input Impedance: 10KΩ/unbalance; 20KΩ/balance.
7. Input Sensitivity: 1.22V full power at 8 Ω.
8. Perfect circuit protection:
(1) DC protection; (2) Subsonic frequency protection; (3) Overloading protection; (4) Short circuit protection; (5) Overheated protection.
9. Two independent channels adopt separate power source, every channel has independent limit, protect and indication circuit.
10. The amplifier has perfect input and output jacks, every channel supplies one XLR input plug and one Φ6.3 stereo plug as balance and unbalance signal input jack, every channel supplies one SPEAKER plug and RCA terminal as sound box's input jack.
11. Adopt silence and high speed fans which can automatic change speed according to radiator's degree as cooling system to insure excellent discharge heat.
12. Available table and rack use because of high strength standard 2U design.
13. Weight: 22kg.
14. Dimensions: 483W * 480D * 89H (mm).

綜合擴音機

1. 輸出功率：150W + 150W。
2. A、B 組喇叭輸出。
3. 具高、低音質調整。
4. 影像輸入：1Vp-p/75hm。
5. 影像輸出：1Vp-p/75hm。
6. 組麥克風輸入及音量調整。
7. 頻率響應：
MIC 20Hz~15KHz。MUSIC: 20Hz~20KHz。
8. 輸入阻抗(靈敏度/阻抗)：MIC 3mv/600Ω。
LD VCR AUX CD 300mv/22KΩ。
9. 輸出阻抗(輸出電壓/輸出阻抗)：2.5V/1KΩ。
10. 具麥克風及音樂之總音量調整。
11. 具備有自動接唱、消音及音域加強功能鍵。
12. 具迴音、REPEAT、DELAY、ECHO 調整。
13. 具放影機、光碟機及點歌機選擇功能鍵。
14. 尺寸：460W * 410D * 165H (mm)。



KTV-600II

Professional Amplifier

1. Output power: 150W + 150W.
2. A, group B speaker outputs.
3. With high and low quality adjustments.
4. Video Input: 1Vp-p/75hm.
5. Video output: 1Vp-p/75hm.
6. Microphone input and volume adjustments.
7. Frequency Response: MIC 20Hz~15KHz. MUSIC: 20Hz~20KHz.
8. Input impedance (Sensitivity / Impedance):
MIC 3mv/600Ω. LD VCR AUX CD 300mv/22KΩ.
9. Output impedance (output voltage/output impedance): 2.5V/1KΩ.
10. The total volume adjustment has a microphone and music.
11. Have automatic access to sing, silencer and range to strengthen the function keys.
12. Has an echo, REPEAT, DELAY, ECHO adjustments.
13. With a video player, CD-ROM drive and select VOD function keys.
14. Dimensions: 460W * 410D * 165H (mm).

綜合擴音機

1. 輸出功率：
300W + 300W (8Ω)。
2. 影像輸入：1Vp-p/75Ω。
3. 影像輸出：1Vp-p/75Ω。
4. A、B 組喇叭輸出。
5. 具高、低音質調整。
6. 3 組麥克風輸入及音量調整。
7. 具麥克風及音樂之總音量調整。
8. 頻率響應：MIC 20Hz~15KHz +0/-3dB; MUSIC 20Hz~15KHz +0/-3dB。
9. 總諧波失真：0.03% (1KHz/3dB/8Ω)。
10. 輸入靈敏電阻：MIC 3mv/10KΩ。KTV. DVD. VCR. AUX 250mv/25KΩ。
11. 輸出位埠阻抗：PRE-output 2V/1KΩ。
12. 輸入靈敏電阻：MIC BASS ±100dB (100Hz) TREBLE ±10dB (10KHz)。
MUSIC BASS ±10dB (100Hz) TREBLE ±10dB (10KHz)。
13. 具備有自動接唱、消音及音域加強功能鍵。
14. 具迴音快慢、迴音長短、迴音大小調整。
15. 具 AUX1/AUX2、放影機、光碟機及點歌機選擇功能鍵。
16. 機器尺寸：460W * 410D * 170H (mm)。



KTV-800

Professional Amplifier

1. Output power: 300W + 300W (8Ω).
2. Video Input: 1Vp-p/75Ω.
3. Video output: 1Vp-p/75Ω.
4. A, group B speaker outputs.
5. With high and low quality adjustments.
6. 3 microphone input and volume adjustments.
7. The total volume adjustment with microphone and music.
8. Frequency response:
MIC 20Hz ~ 15KHz +0/-3dB; MUSIC 20Hz ~ 15KHz +0/-3dB.
9. Total Harmonic Distortion: 0.03% (1KHz/3dB/8Ω).
10. Input sensitivity resistance:
MIC 3mv/10KΩ. KTV. DVD. VCR. AUX 250mv/25KΩ.
11. Bit output port impedance: PRE-output 2V/1KΩ.
12. Amp input sensitivity resistance:
MIC BASS ± 100dB (100Hz) TREBLE ± 10dB (10KHz).
MUSIC BASS ± 10dB (100Hz) TREBLE ± 10dB (10KHz).
13. Have automatic access to sing, silencer and range to strengthen the function keys.
14. Speed with echo, echo duration, echo resizing.
15. Has AUX1/AUX2, video player, CD-ROM drive and select VOD function keys.
16. Dimensions: 460W * 410D * 170H (mm).